

Input / Output Unit *Product Datasheet*

Key Features

- Dual band 868MHz operation
- 2x supervised inputs
- 2x voltage free outputs, rated 2A@24V
- Third party EN certified
- Optional 230Vac switching Auxiliary Relay Module available



Product Overview












The FireCell Wireless Input Output unit is quick and easy to install and offers individual addressing at the Fire Control Panel.

Features include; two supervised inputs and two voltage free outputs rated 2A@24V, whilst using only one address on the system.

This device is third party EN certified and compatible with the EMS FireCell system, EMS Fusion Radio Loop Module (RLM) and EMS Wireless Zone Monitor (WZM).

A 230Vac switching Auxiliary Relay Module is also available, for use in conjunction with this device. Refer to doc ref TSD058 for full technical specifications.

Technical Data

 -10°C to 55°C	 0 - 14 dBm (auto adjusting)	 CE 10 0359-CPR-0039
 6x AA alkaline batteries	 2x 2A @ 24Vdc rated outputs	 EN EN54-18 & EN54-25
 IP65, indoor use only	 120mm(W) 240mm(H) 60mm(D)	 FC-610-001 <i>Dual I/O Unit</i> FC-620-001 <i>Auxiliary Relay Module</i> (for use with FC-610-001)
 868MHz	 0.95kg	