



## Wireless Sounder Product Datasheet

## Key features

- Dual band 868 MHz operation
- 32 selectable tones
- Integrated audio monitoring
- Sounder volume control
- Anti tamper locking mechanism
- Third party EN approved



## Product overview

The FireCell Wireless Sounder is quick and easy to install, offering individual addressing at the fire control panel. This device comprises of a sounder and a wireless sounder base.

Features include dual band 868 MHz operation, auto adjusting power output, 32 selectable tones, integrated audio monitoring, volume control and anti-tamper locking mechanism.

This device is third party EN certified and compatible with the EMS FireCell system, EMS Fusion Radio Loop Module (RLM) and EMS Wireless Zone Monitor (WZM).

## Technical data



-10 to 55 °C



3x AA Alkaline batteries (Panasonic LR6AD Powerline / Varta 4006 Industrial) & 3x  $\mathbb{C}$ Alkaline (Panasonic batteries LR14AD Powerline / Varta 4014 Industrial)



IP54, indoor use only



868 MHz



0 to 14 dBm (auto adjusting)



120 x 125 mm (Ø x D)



 $0.65 \, \text{kg}$ 



X (signalling protocol)



Up to 99 dB(A) at 1 m (as dispatched)



**C€10** 0359-CPR-0022



EN54-3 & EN54-25



FC-171-001 White Wireless Sounder Base only

FC-171-002 Red Wireless Sounder Base only

FC-172-001 White Sounder only

FC-172-002 Red Sounder only

FC-173-002 Red Sounder Visual Indicator only

FC-178-002 Red Visual Indicator only