

# Wireless Call Point (KAC front)

## Product Datasheet

### Key features

- Dual band 868 MHz operation
- Fire indication LED
- Resettable element
- Anti tamper locking
- Protective cover
- Third party EN certified



### Product overview












The FireCell Wireless Call Point is quick and easy to install and offers individual addressing at the fire control panel.

Features include dual band 868 MHz operation, auto adjusting power output, fire indication LED, resettable element, anti tamper and a test key.

A transparent hinged cover is also included, for protection against accidental operation in busy environments.

This device is third party EN certified and compatible with the EMS FireCell system, EMS Fusion Radio Loop Module (RLM) and EMS Wireless Zone Monitor (WZM).

### Technical data

- |   |  |
|---|--|
|  -10 to 55 °C   |  89 x 92 x 70 mm (W x H x D)                          |
|  6 x AA Alkaline ( <i>Panasonic LR6AD Powerline / Varta 4006 Industrial</i> ) |  0.4 kg   |
|  IP24, indoor use only  |  <b>CE10</b><br>0359-CPR-0038                         |
|  868 MHz  |  <b>EN</b> EN54-11 & EN54-25                          |
|  0 to 14 dBm ( <i>auto adjusting</i> )  |  FC-200-002<br><i>Wireless Call Point (KAC Front)</i> |
|  X ( <i>signalling protocol</i> )   |  |