

WIRELESS CALL POINT (APOLLO FRONT)

Product datasheet

Key features

- Dual band 868 MHz operation
- Fire indication LED
- Resettable element
- Anti tamper locking
- Protective cover
- Third party EN certified



Product overview













The FireCell wireless call point is quick and easy to install and offers individual addressing at the fire control panel.

Features include dual band 868 MHz operation, auto adjusting power output, fire indication LED, resettable element, anti tamper and a test key.

A transparent hinged cover is also included, for protection against accidental operation in busy environments.

This device has third party EN certification and is compatible with the EMS FireCell system including the Fusion RLM.

Technical data

-  -10 to 55 °C
-  6 x AA Alkaline (*Panasonic LR6AD Powerline / Varta 4006 Industrial*)
-  IP24, indoor use only
-  868 MHz
-  Up to 1250 m (*clear line of site*)*
-  0 to 14 dBm (*auto adjusting*)
-  X (*signalling protocol*)
-  90 x 98 x 72.5 mm (*W x H x D*)
-  0.35 kg
-  CE
-  DoP 0359-CPR-00694
-  EN EN54-11 & EN54-25
-  FC-200-003
WIRELESS CALL POINT
(APOLLO FRONT)

***Line of sight refers to the maximum distance over which radio frequency signals can travel in a direct, unobstructed path between transmitter and receiver.**