

DUAL INPUT / OUTPUT DEVICE



















Product datasheet

Key features

- Fully wireless communication with WZM
- Quick and easy to install
- Two resistor monitored inputs
- Two voltage free outputs
- For connection to remote fire devices



Technical data

 Operating / storage without batteries: -10 to +55 °C	 14 dBm / 25 mW	  
Storage with batteries: -10 to +30 °C	 X5 (signalling protocol)	 
 3 x AA ER14505M lithium thionyl chloride batteries (Fanso or Titus)	 2x resistor monitored inputs	 0359-CPR-00269
 Indoor use only	 2x 1A at 30 VDC rated outputs	 EN54-13, EN54-18 & EN54-25
 868 MHz	 150 x 200 x 55 mm (W x H x D)	 SC-23-0220-0001-WZ
	 0.45 kg	