

Wireless Push Button Panic Alarm c/w Air Switch

Product Datasheet

Key Features

- Complete with air switch
- Fully wireless
- Fully addressable
- LED indication
- IP65 enclosure
- Up to 1 Year battery life



Product Overview


The wireless push button panic alarm c/w air switch has been designed as a splash proof attack alarm transmitter prompted by demand from the leisure centre industry and is ideal for use in all types of industrial or commercial premises where staff need the security of a fixed attack alarm.


As the system is devoid of interconnecting wiring, any alteration can be carried out quickly and inexpensively. False alarms caused by damage to traditional 24-hour live personal attack wiring circuits are totally eliminated.


Alarm transmissions are sent by pressing the push button located on the front of the unit or by pressing the connected air switch. The air switch is typically fitted on the other side of the wall and often in Saunas.


When installed in conjunction with the EMS Iris+ receiver, up to 256 individual transmitters can be individually identified by the receiver.


Technical Data

 -10 to 55 °C
Up to 75% non-condensing


 4x AAA alkaline batteries

 7920/AS (Wireless push button panic alarm c/w air switch)

 120(h) x 80(w) x 55(d)mm

 UHF 458.5 - 459.5MHz
25 KHz (MPT 1329)
1mW ERP

 0.3kg

 EN50131 class 2 grade 2